## INVESTIGATION OF THE BACK SIDE PASSIVATION LAYER OF SCREEN PRINTED BIFACIAL SILICON SOLAR CELLS

Sebastian Gloger, Stefanie Riegel, Bernd Raabe, Giso Hahn University of Konstanz, Department of Physics, 78457 Konstanz, Germany Email: sebastian.gloger@uni-konstanz.de, phone: +49 7531 88 2074, fax: +49 7531 88 3895

ABSTRACT: This work compares the back side passivation quality of bifacial silicon (Si) solar cells with boron back-surface-field (B-BSF) of different sheet resistances. The influence of the thickness of an additional dry thermal silicon dioxide (SiO<sub>2</sub>) to passivate the surface of the B-BSF is also investigated. The passivation quality is compared in two experiments: First Si lifetime samples with boron (B) emitter are passivated and their emitter saturation current densities ( $J_{0E}$ ) are determined with quasi-steady-state photoconductance (QSSPC) measurements after every process step. Secondly large area bifacial solar cells with different base doping are processed. The cell parameters are determined by illuminated current-voltage (IV) characteristics and the effective minority charge carrier diffusion lengths ( $L_{eff}$ ) are calculated with a model [1] using the internal quantum efficiencies (IQE) from spectral response measurements. The optimum B-BSF sheet resistance for the bifacial cell concept used is found to be 60 Ohm/sq. The optimum value of the thickness of the SiO<sub>2</sub> layer for additional surface passivation is found to be in the range of 19-30 nm dependent on the base doping.

Keywords: passivation, back-surface-field, bifacial

### 1 INTRODUCTION

The widely used screen printing solar cell process causes problems like recombination at the back side (BS) and wafer bow, especially when applied to thin wafers. To avoid the problems of the full area metallization of the BS a B-BSF and a finger grid can be used, allowing also illumination of the solar cell from the BS. Theoretical calculations predict that the passivation quality of a BSF is determined by its doping depth and density as well as by the base doping, the carrier mobilities and diffusion lengths [2]. To examine the interrelation between the passivation quality and the doping profile experimentally, we process symmetrical lifetime samples and bifacial solar cells with different B-BSF doping profiles. As it is known, that silicon nitride  $(SiN_x)$  is not suitable for the passivation of contacted p<sup>+</sup>-Si surfaces [3], we use SiO<sub>2</sub>/SiN<sub>X</sub> stacks for back side passivation. We investigate the influence of the thickness of the SiO<sub>2</sub> layer on the passivation quality.

#### 2 LIFETIME SAMPLES

To determine the passivation quality of different B-BSF doping profiles, emitter saturation currents are measured with the QSSPC technique on float-zone (FZ) Si wafers. Therefore, phosphorous doped n-type wafers with a size of  $50^2$  mm<sup>2</sup>, a thickness of 550 µm and a resistivity R<sub>Bulk</sub> of 1 Ohmcm are symmetrically processed using the following steps:

A boron emitter is created by a borontribromide (BBr<sub>3</sub>) diffusion. This p<sup>+</sup>-emitter has a sheet resistance  $R_S$  of 34, 60 or 82 Ohm/sq and a thickness of 0.4-0.9 µm dependent on  $R_S$ . The boron glass is removed in a diluted hydrogen fluoride (HF) solution. For additional passivation a thermal oxidation is carried out. The thickness of the SiO<sub>2</sub> layer is 23-26 nm. As antireflection coating and hydrogen source a plasma-enhanced chemical vapor deposited (PECVD) hydrogen rich silicon nitride (SiN<sub>x</sub>:H) layer with a thickness of  $\sim$  100 nm is deposited on both wafer sides (see figure 1). To determine the influence of the thermal impact of a

phosphoryl chloride (POCl<sub>3</sub>) diffusion in a solar cell process the samples are subjected to a high temperature step with the temperature and duration typical for a POCl<sub>3</sub> diffusion.


QSSPC measurements are performed on samples of all three sheet resistances after emitter diffusion, after thermal oxidation, after  $SiN_X$ :H layer deposition without firing and after the high temperature step simulating a POCl<sub>3</sub> diffusion. The values for  $J_{0E}$  are determined in high injection [4].



Figure 1: Passivated n-type silicon sample with Bemitter,  $SiO_2$  and  $SiN_X$ :H layer.

## 3 EXPERIMENTAL RESULTS: SAMPLES

The J<sub>0E</sub> values obtained from QSSPC measurements are shown in figure 2. Directly after BBr<sub>3</sub> diffusion the  $J_{0E}$  mean values for the different diffusions are in the range from 4800 to 17000 fA/cm<sup>2</sup>. The thermal oxidation reduces  $J_{0E}$  to mean values from 1600 to 2100 fA/cm<sup>2</sup>. After the PECVD SiN<sub>X</sub>:H deposition the J<sub>0E</sub> mean values are in the range from 300 to 900 fA/cm<sup>2</sup> this means passivation with a SiO<sub>2</sub> layer is improved by the PECVD SiN<sub>x</sub>:H deposition. The following high temperature step with the temperature and duration typical for a POCl<sub>3</sub> diffusion increases J<sub>0E</sub> due to a loss of hydrogen at the Si/SiO2 interface to mean values from 600 to 1100 fA/cm<sup>2</sup>. After every process step the 60 Ohm/sq diffusion obtained the lowest mean J<sub>0E</sub> and the 34 Ohm/sq diffusion the highest. The best passivation is achieved with a B-emitter doping of 60 Ohm/sq and a SiO<sub>2</sub>/SiN<sub>X</sub>:H stack. This combination leads on the best sample to a  $J_{0E}$  of 280 fA/cm<sup>2</sup>.



**Figure 2:**  $J_{0E}$  values of the lifetime samples after a BBr<sub>3</sub> diffusion, a thermal oxidation, PECVD SiN<sub>X</sub>:H deposition and a high temperature step typical for a POCl<sub>3</sub> diffusion.

### 4 BIFACIAL SILICON SOLAR CELLS

To determine the quality of the back side passivation we produce bifacial solar cells with different B-BSF doping profiles ( $R_s$ : 10, 34, 60, 82 Ohm/sq) and SiO<sub>2</sub> layers of different thickness (18-54 nm). The IV characteristics and IQEs of the cells are measured and the corresponding  $L_{eff}$  is extracted using the model of B. Fischer [1].

The solar cells are processed based on B-doped ptype Czochralski (Cz) Si wafers with a size of  $125^2$  mm<sup>2</sup> semisquare, a thickness of 220-250 µm and a R<sub>Bulk</sub> of 1-5 Ohmcm. First the back side is doped with a p<sup>+</sup>-B-BSF with a R<sub>S</sub> of 10, 34, 60 or 82 Ohm/sq and in the following passivated by a thermal oxide of 18-54 nm and a PECVD SiN<sub>X</sub>:H deposition. Subsequent the front side is processed with a random pyramid texture, a standard POCl<sub>3</sub> emitter a PECVD SiN<sub>X</sub>:H and a screen printed Ag grid. The back side metallization is formed by screen printing an Ag/Al finger grid (see figure 3 and figure 4).




Figure 3: Screen printed bifacial solar cell concept.




Figure 4: Bifacial solar cell process.

# 5 EXPERIMENTAL RESULTS: SOLAR CELLS

#### 5.1 IV measurements

IV and also spectral response and reflectivity measurements of the bifacial cells are performed on a polished brazen chuck with  $\sim 90$  % reflectivity for wavelengths > 1000 nm. Thus light transmitting the cell is reflected by the chuck and re-enters the cell from the back side.

On 2-5 Ohmcm  $R_{\text{Bulk}}$  feedstock  $V_{\text{OC}}$  values of 638-639 mV under front side illumination (FS) and 636-637 mV under back side illumination (BS) are achieved with a B-BSF R<sub>s</sub> of 34, 60 and 82 Ohm/sq. The mean  $V_{OC}$  values of the 60 and 82 Ohm/sq cells are 635-636 mV (FS) and 632-634 mV (BS). For the 34 Ohm/sq cells the mean V<sub>OC</sub> values are 630-632 mV (FS) and 627-630 mV (BS). On 1 Ohmcm  $R_{Bulk}$  feedstock  $V_{OC}$  values of 634 mV (FS) and 626 mV (BS) are achieved with a B-BSF R<sub>s</sub> of 60 Ohm/sq. Due to a not optimal front surface texture on the previously NaOH etched FS (see [5]) the best short-circuit current density (J<sub>SC,FS</sub>) is 35.2 mA/cm<sup>2</sup>. The back surface is not textured and the thickness of the back antireflection coating (ARC) is less optimized. Hence the best J<sub>SC,BS</sub> is 32.9 mA/cm<sup>2</sup>. The best values are both achieved with a B-BSF R<sub>S</sub> of 60 Ohm/sq. The fill factors (FF) of all the cells are reduced on account of a not optimized metallization featuring interrupted fingers and not optimal contacting. This is ascertained by electroluminescence measurements. The highest FF measured is 75.8 % also on a cell with 60 Ohm/sq B-BSF sheet resistance. The best efficiency  $(\eta)$  achieved under front side (FS) illumination is 16.4 % and 14.4 % under back side (BS) illumination, both with 60 Ohm/sq B-BSF  $R_S.$  The cell with the best  $\eta_{BS}$  shows also the best ratio  $\eta_{BS}/\eta_{FS}$  of 93 %.

#### 5.2 Spectral response measurements

IQE (see figure 5) and  $L_{eff}$  are calculated from the measured external quantum efficiency (EQE) and reflectivity with a computer program written by B. Fischer [1] containing models of P. A. Basore [6] and R. Brendel [7]. For the calculation of  $L_{eff}$  the wavelength range from 600 to 720 is approximated with a dead layer model [1] and the wavelength range from 760 to 920 nm is approximated with a model of P. A. Basore [6].  $L_{eff}$  is dependent on the doping level of the base since recombination in the base and BSF band bending are affected by the level of base doping. Due to reflection from the chuck for long wavelengths the IQE is increased compared to an IQE of the same cell measured on an absorbing chuck.

The values of L<sub>eff</sub> show that the quality of the BS passivation depends on the R<sub>S</sub> of the B-BSF and on the thickness of the SiO<sub>2</sub> layer. For all solar cells processed in this work with a R<sub>Bulk</sub> of 1-5 Ohmcm a B-BSF with a R<sub>S</sub> of 60 Ohm/sq leads to the highest mean L<sub>eff</sub> values of 500-1000  $\mu$ m for a R<sub>Bulk</sub> of 1 Ohmem and 3000-3400  $\mu$ m for a R<sub>Bulk</sub> of 2-5 Ohmcm. On 2-5 Ohmcm R<sub>Bulk</sub> feedstock the cells with a B-BSF of 82 Ohm/sq R<sub>S</sub> achieve mean  $L_{eff}$  values of 2100-2500  $\mu$ m and the cells with a B-BSF of 34 Ohm/sq R<sub>S</sub> achieve mean L<sub>eff</sub> values of 2000-2100 µm. The cells fabricated from 1 Ohmcm  $R_{Bulk}$  feedstock obtain mean  $L_{eff}$  values of 200-700  $\mu m$ with a B-BSF of 34 Ohm/sq R<sub>s</sub> and 200-600 µm without B-BSF. The cells with a base resistivity of 1 Ohmcm are passivated best with an additional SiO<sub>2</sub> layer of 24-30 nm independent of the B-BSF sheet resistance. For those with a base resistivity of 2-5 Ohmcm an additional SiO<sub>2</sub> layer of 19-21 nm leads to the highest mean Leff independent of the B-BSF sheet resistance (see figure 6). The best passivation of all the cells fabricated is achieved using a B-BSF of 60 Ohm/sq and a SiO<sub>2</sub> layer of 20 nm thickness. All cells have an additional SiN<sub>X</sub> layer of 75 nm thickness.





Figure 5: Internal quantum efficiency of the best passivated cell plotted against the wavelength. The FS IQE for long wavelengths is high (64 % @ 1100 nm) and the BS IQE shows nearly no decrease going from 900 to 500 nm, indicating a good surface passivation.



**Figure 6:**  $L_{eff}$  plotted against the sheet resistance of the B-BSF of the cells. The mean values are shown for different thicknesses of the SiO<sub>2</sub> layer.

# 6 CONCULSION

Our measurements verify the influence of the doping depth and concentration on the passivation quality of a B-BSF. Furthermore, we can demonstrate the influence of the SiO<sub>2</sub> layer on the passivation quality. Optimum values for the bifacial cell concept are found to be 60 Ohm/sq  $R_s$  for the B-BSF doping and 19-21 nm for the SiO<sub>2</sub> layer thickness.

### 7 ACKNOWLEDGEMENTS

The authors would like to thank S. Ohl, B. Rettenmaier and L. Rothengaß for their support during cell processing.

The financial support from the BMU project 0325079 is gratefully acknowledged in particular for the sample characterization equipment.

# 8 REFERENCES

- B. Fischer, Loss analysis of crystalline silicon solar cells using photoconductance and quantum efficiency measurements, Diss. Univ. Konstanz (2003).
- [2] M. P. Godlewski et al., Low-high junction theory applied to solar cells, Proc. 10<sup>th</sup> PVSC (1973), Palo Alto, p. 40.
- [3] S. Dauwe et al., Experimental evidence of parasitic shunting in silicon nitride rear surface passivated solar cells, Prog. Photovolt: Res. Appl. 10, 2002, p. 271.
- [4] A. Cuevas et al., Applications of the quasi-steadystate photoconductance technique, Proc. 2<sup>nd</sup> WPVSEC (1998), Vienna, p. 1236.

- [5] S. Riegel et al., Comparison of the passivation quality of boron and aluminum BSF for wafers of varying thickness, this conference.
- [6] P. A. Basore, Extended spectral analysis of internal quantum efficiency, Proc. 23<sup>rd</sup> IEEE PVSC (1993), Louisville, p. 147.
- [7] R. Brendel et al., Effective diffusion length for minority carriers in solar cells as determined from internal quantum efficiency analysis, J. Appl. Phys. 85, 1999, p. 3634.